

## SPECIFICATIONS

## ELECTRICAL

Current dissipation : 110 mA  
 Power Consumption : 1.08 W  
 Operating power : DC 12V  
 Maximum serial connection : 25 modules  
 Electronic dimming control supported  
 Constant current drive, Reverse voltage protection

## THERMAL

Cooling : Ambient air  
 Maximum operating temperature : 50°C  
 Minimum operating temperature : -20°C  
 Maximum storage temperature : 60°C  
 Minimum storage temperature : -20°C

42,500H  
LIFETIME


IP63

CONSTANT CURRENT  
DRIVING SYSTEM

REVERSE VOLTAGE  
PROTECTION

DC12V

## PHYSICAL



## PRECAUTIONS



Use precautions to avoid damages to the product or injuries of users. Any actions against following contents will cause serious issues such as malfunction, electric shock, or burn.



USE DC12V ONLY



DO NOT USE AC INPUT



Do not perform actions listed below

- Alter or modify
- Touch LED lamps with sharp objects
- Put glue or silicon over the LED lamps



Do not cut or rejoin wires while product is connected with live power source



Maximum driver quantity per serial connection is limited. Failure causes overload of current and damages to the product



Avoid performing installation under rain or high humidity for outdoor use



Refer to 'WIRE THICKNESS' table to use proper wire thickness between SMPS and the first LED module  
 Failure will cause dimmed output



Do not use the product under circumstances listed below


- High temperature spots over 60°C (140°F)
- Spots draw extreme moisture or dust
- Spots have corrosive gas or highly effected by electromagnetic field



Cable length between SMPS and the first LED module is limited. Refer to 'CONNECTION WITH POWER SUPPLY' on page 2


## PREPARATION

## TOOLS REQUIRED




Wire Stripper, Drill, Screw Driver, Wiper

## SUPPLIES REQUIRED




Wire Nuts, Cable Ties, IDC Connectors, VCTF(PLTC) Cable, (Optional : Silicon and Screws)


## PREPARE CHANNELS




1. Clean moisture and dust inside



2. Make holes



3. Use bushing to protect wires




1. Wipe out dust, water, and oil inside. 3M tape will come off easily if product is mounted on uncleaned surfaces.
2. Make holes for wires from modules to SMPS.
3. Without bushins, wires will easily be cut and short-circuit will occur.  
 \*Use white paint inside the channels for better reflection


## LAYOUT DENSITY GUIDELINES

Use recommended length for pitch between each module to achieve optimum lighting output while maintaining lowest unit cost. Failure or misplacing will cause dimmed spots or uneven appearance of light on the surface.

### RECOMMENDED CENTER OF MODULE PITCH PER MINIMUM DEPTH




### RECOMMENDED LAYOUT DENSITY PER CHANNEL WIDTH



## CONNECTION GUIDE

Maximum driver quantity per serial connection is limited. Using more quantity per run will cause overload from SMPS which damages all connected products. This will cause voltage drop and also dimmed lighting output.



*\*When mixed run should occur, count 1(one) for C0230, C0320, and C0340  
\*\*Must count C0640 as 2(two) and keep the total counts under 50*

## CONNECTION WITH POWER SUPPLY

### EXTENSION OF POWER SUPPLY LEAD WIRES


Model Name	PSGE-0030-12	PSGE-0060-12	PSGE-0120-12	PSGE-0600-12**	PSGE-1000-12**
Output (W)	30W	60W	120W	600W	1000W
Output (A)	2.5A	5A	10A	50A	83A
STAR C0640	19pcs	37pcs	73pcs	365pcs	610pcs
Recommended Extension Wire	VCTF1.25 AWG18	VCTF2.0 AWG14	VCTF2.0 AWG12	VCTF5.5 AWG4	VCTF8.0 AWG2
Maximum Length	5M (15FT)	5M (15FT)	5M (15FT)	15M (50FT)	15M (50FT)

\*Maximum quantity for S-LED is based on 85% of specified capacity of power supplies for extended lifespan

\*\*PSCS-0600-12, PSCS-1000-12 are not weather-proof

Equip with protective box for outdoor use and the box should have ventilating holes

## 1. DETERMINE LAYOUT



### TROUBLE SHOOTING

Entire sign or leg does not light after complete installation.	Check connection from power supply lead to first module. Make sure polarity of connections made at the power supply lead and any jumper wire is correct. Power supply outputs should be connected red-to-red and white-to-white.
Still does not light.	Check output voltage of power supply using a voltmeter. The output voltage should be $12.0\text{VDC} \pm 0.5\text{VDC}$ . If there is no output voltage, have a licensed electrician check input voltage. Make sure power supply is connected correctly and getting primary power. If power supply is connected properly and getting primary power and there is still no output voltage, try a different power supply.
Still does not light.	If power supply is getting primary power and the modules do not light, there may be a short in the secondary wiring. Check all connections and cap all loose wires.
Beginning of a leg lights, but the entire leg does not light or lights intermittently.	The primary cause of a portion of a S-LED leg not lighting or lighting intermittently is a bad connection or reverse polarity connection between the modules that light and the modules that don't light. Check this connection.
One module does not light, but all others in the leg light.	S-LED is designed so if one module fails, it will not cause the entire sign or leg to go out. If one module does not light, but all others in the leg do, replace this module with a new one.
All modules light, but some of them are dimmed.	Check each run has no more than maximum number of modules. Also ensure that type of the extension wire from SMPS to the first module is correct. If wires are not thick enough to transmit current from SMPS, this will cause voltage drop and will dim the modules at
Dark spots or dimmed spots occur.	Channel depth is too low, or center distance between modules is too far. Refer to 'LAYOUT DENSITY GUIDELINES' for more information.
Still has spots.	Covering acrylic is not intended for LED illumination. Use light diffusing acrylic sheets which are specially made for LED light source.